

## Voltage Transducer LV 200-AW/2/SP1

For the electronic measurement of voltages : DC, AC, pulsed..., with a galvanic isolation between the primary circuit (high voltage) and the secondary circuit (electronic circuit).

$$I_{PN} = 20 \text{ mA}$$

$$V_{PN} = 100 \dots 5000 \text{ V}$$



### Electrical data

$I_{PN}$	Primary nominal r.m.s. current	20	mA
$I_P$	Primary current, measuring range	0 .. $\pm 40$	mA
$R_M$	Measuring resistance	$R_{M \min}$ $R_{M \max}$	
	with $\pm 15 \text{ V}$	@ $\pm 20 \text{ mA}_{\max}$	0 90 $\Omega$
		@ $\pm 40 \text{ mA}_{\max}$	0 30 $\Omega$
	with $\pm 24 \text{ V}$	@ $\pm 20 \text{ mA}_{\max}$	60 170 $\Omega$
		@ $\pm 40 \text{ mA}_{\max}$	60 70 $\Omega$
$I_{SN}$	Secondary nominal r.m.s. current	100	mA
$K_N$	Conversion ratio	10000 : 2000	
$V_C$	Supply voltage ( $\pm 10 \%$ )	$\pm 15 \dots 24$	V
$I_C$	Current consumption	30 (@ $\pm 24 \text{ V}$ ) + $I_S$	mA
$V_d$	R.m.s. voltage for AC isolation test, 50 Hz, 1 mn	12 <sup>1)</sup>	kV
		1 <sup>2)</sup>	kV
$V_e$	R.m.s. voltage for partial discharge extinction @ 10 pC	4800	V

### Accuracy - Dynamic performance data

$X_G$	Overall Accuracy @ $I_{PN}$ , $T_A = 25^\circ\text{C}$	$\pm 0.5$	%
$\epsilon_L$	Linearity error	$< 0.1$	%
$I_O$	Offset current @ $I_P = 0$ , $T_A = 25^\circ\text{C}$	Typ	Max
$I_{OT}$	Thermal drift of $I_O$ - $25^\circ\text{C} \dots +70^\circ\text{C}$	$\pm 0.4$	$\pm 0.7$ mA
$t_r$	Response time <sup>3)</sup> @ 90 % of $V_{PN}$	20 .. 100	$\mu\text{s}$

### General data

$T_A$	Ambient operating temperature	- 25 .. + 70	$^\circ\text{C}$
$T_S$	Ambient storage temperature	- 40 .. + 85	$^\circ\text{C}$
$R_P$	Primary coil resistance @ $T_A = 25^\circ\text{C}$	450	$\Omega$
$R_S$	Secondary coil resistance @ $T_A = 70^\circ\text{C}$	30	$\Omega$
$m$	Mass	1.6	kg
	Standards	EN 50178(01.10.97)	

Notes : <sup>1)</sup> Between primary and secondary + shield

<sup>2)</sup> Between secondary and shield

<sup>3)</sup>  $R_1 = 50 \text{ k}\Omega$  (L/R constant, produced by the resistance and inductance of the primary circuit).

### Features

- Closed loop (compensated) voltage transducer using the Hall effect
- Insulated plastic case recognized according to UL 94-V0
- Accessible electronic circuit
- Shield between primary and secondary circuit.

### Special feature

- $V_d = 12 \text{ kV}^{1)}$ .

### Principle of use

- For voltage measurements, a current proportional to the measured voltage must be passed through an external resistor  $R_1$  which is selected by the user and installed in series with the primary circuit of the transducer.

### Advantages

- Excellent accuracy
- Very good linearity
- Low thermal drift
- High immunity to external interference.

### Applications

- AC variable speed drives and servo motor drives
- Static converters for DC motor drives
- Battery supplied applications
- Uninterruptible Power Supplies (UPS)
- Power supplies for welding applications.

030915/6

